



ABN 43 064 478 842

231 Osborne Avenue Clayton South, VIC 3169
PO Box 1548, Clayton South, VIC 3169
t 03 9265 7400 f 03 9558 0875
freecall 1800 680 680
www.tmgtestequipment.com.au

Test & Measurement

- > sales
- > rentals
- > calibration
- > repair
- > disposal

Complimentary Reference Material

This PDF has been made available as a complimentary service for you to assist in evaluating this model for your testing requirements.

TMG offers a wide range of test equipment solutions, from renting short to long term, buying refurbished and purchasing new. Financing options, such as Financial Rental, and Leasing are also available on application.

TMG will assist if you are unsure whether this model will suit your requirements.

Call TMG if you need to organise repair and/or calibrate your unit.

If you click on the "Click-to-Call" logo below, you can call us for FREE!

TMG Corporate Website

TMG Products Website



Click-to-Call
TMG Now



Product Lifecycle Management System

Disclaimer:

All trademarks appearing within this PDF are trademarks of their respective owners.



LeCroy Digital Oscilloscopes

Get the Complete Picture

AP033 Active Differential Probe

**Preliminary
Datasheet**

LEADING FEATURES

- **500 MHz Bandwidth**
- **x10 Gain to ÷10 Attenuation Range**
- **10,000: 1 DC CMRR**
- **Low 4 nV/ $\sqrt{\text{Hz}}$ Noise**
- **2 pF/Side Input C**
- **200 $\mu\text{V}/\text{div}$ - 10 V/div**
- **Input ESD Protection**
- **Autobalance Feature**

The AP033 is a high-performance active differential probe. High bandwidth, excellent common mode rejection ratio (CMRR) and low-noise floor make the AP033 ideal for applications such as disk drive design and failure analysis as well as wireless and data communication design.

Fully Integrated: With the ProBus™ interface, the AP033 becomes an integral part of the oscilloscope. The probe sensitivity and offset can be controlled from the oscilloscope front panel, the probe front panel, or by using remote control commands (GPIB or RS-232).

Sensitivity, offset, input capacitance, and common mode voltage range are displayed on the oscilloscope screen. When used with a LeCroy digital oscilloscope, no external power supply is required.

Wide Dynamic Range: The AP033 provides a range of sensitivities from x10 gain to ÷10 attenuation (even ÷100 with plug-on attenuator) for diverse signals. The sensitivity can be adjusted continuously from 200 $\mu\text{V}/\text{div}$ to 1 V/div, when used with a LeCroy oscilloscope.



LeCroy

At high sensitivities, the x10 GAIN and the ÷1 ATTENUATION are selected. This produces 4 nV/ $\sqrt{\text{Hz}}$ input noise, ± 5 V of common mode voltage range (CMVR), and ± 400 mV of DC differential offset. At lower sensitivities, the x1 GAIN and ÷10 ATTENUATION are selected, resulting in ± 50 V CMVR and ± 4 V of differential offset.

The input capacitance is just 2 pF/side (1 pF differential) whenever the ÷10 ATTENUATION is selected. Deflection factors of 2 mV/div to 1 V/div can be obtained with only 2 pF/side input capacitance and ± 50 V CMVR.

DC CMRR is greater than 10,000:1 (80 dB) in both ATTENUATION settings.

OFFSET up/down buttons allow OFFSET control from the probe amplifier body. Momentarily holding both buttons will zero the OFFSET.

A supplied AC coupling capacitor head (0.1 μF) allows operation with large common-mode or differential DC inputs.

The input attenuator automatically changes from ÷1 to ÷10 when too much common-mode signal is sensed. This and a fast input protection circuit also serve to protect the input from potentially damaging signals. When the probe is removed or the power is turned off, the ÷10 ATTENUATION is automatically invoked, leaving the inputs protected when not in use.

GAIN AND ATTENUATION SELECTIONS

The AP033 consists of a probe head with ÷1 or ÷10 attenuation and an amplifier body which attaches to the scope front panel. The amplifier gain can be either x1 and x10. Both the probe head attenuator and amplifier gain are controlled through the ProBus interface. Normally the GAIN and ATTENUATION selections are accomplished by the oscilloscope as shown in the table below.

There are two ways of obtaining x1 gain from the AP033: x1 GAIN with ÷1 ATTENUATION, or x10 GAIN with ÷10 ATTENUATION with different input capacitance, CMVR, and noise performance. The oscilloscope selects the latter of these two options (as shown below) to provide minimum input capacitance and maximum common-mode dynamic range while still leaving low noise operation available at the highest sensitivity.

By using the probe amplifier body control to override the automatic selection, the x1 GAIN with ÷1 ATTENUATION option is readily available for 10 mV, 20 mV and 50 mV/div. CMVR is ± 5 V, input capacitance is 5 pF, and noise is 9 nV/ $\sqrt{\text{Hz}}$. Similarly, x10 GAIN and ÷10 ATTENUATION can be selected at 2 mV/div and 5 mV/div for 2 pF input C and ± 50 V CMVR. The oscilloscope displays the correct deflection factor in all cases.

Using the supplied accessory plug-on attenuator head, gain selections from 100 mV/div to 10 V/div are available.

Deflection Factor	Scope Deflection Factor	AP033 Attenuation	AP033 Gain	CM Range	Input C	Maximum Offset Range	Input Noise
200 $\mu\text{V}/\text{div}$	2.0 mV/div	÷1	X10	± 5 V	5 pF	± 400 mV	4 nV/ $\sqrt{\text{Hz}}$
500 $\mu\text{V}/\text{div}$	5.0 mV/div	÷1	X10	± 5 V	5 pF	± 400 mV	4 nV/ $\sqrt{\text{Hz}}$
1.0 mV/div	10.0 mV/div	÷1	X10	± 5 V	5 pF	± 400 mV	4 nV/ $\sqrt{\text{Hz}}$
2.0 mV/div	20.0 mV/div	÷1	X10	± 5 V	5 pF	± 400 mV	4 nV/ $\sqrt{\text{Hz}}$
5.0 mV/div	50.0 mV/div	÷1	X10	± 5 V	5 pF	± 400 mV	4 nV/ $\sqrt{\text{Hz}}$
10.0 mV/div	10.0 mV/div	÷10	X10	± 50 V	2 pF	± 4 V	40 nV/ $\sqrt{\text{Hz}}$
20.0 mV/div	20.0 mV/div	÷10	X10	± 50 V	2 pF	± 4 V	40 nV/ $\sqrt{\text{Hz}}$
50.0 mV/div	50.0 mV/div	÷10	X10	± 50 V	2 pF	± 4 V	40 nV/ $\sqrt{\text{Hz}}$
100 mV/div	10.0 mV/div	÷10	X1	± 50 V	2 pF	± 4 V	40 nV/ $\sqrt{\text{Hz}}$
200 mV/div	20.0 mV/div	÷10	X1	± 50 V	2 pF	± 4 V	40 nV/ $\sqrt{\text{Hz}}$
500 mV/div	50.0 mV/div	÷10	X1	± 50 V	2 pF	± 4 V	40 nV/ $\sqrt{\text{Hz}}$
1.00 V/div	100 mV/div	÷10	X1	± 50 V	2 pF	± 4 V	40 nV/ $\sqrt{\text{Hz}}$

INPUT CHARACTERISTICS

The input capacitance is modeled by 2 pF to ground from each input plus 0.20 pF from input to input when the $\div 10$ ATTENUATION is selected. This is equivalent to 1.20 pF differential input capacitance. With $\div 1$ ATTENUATION, the differential input capacitance is 2.7 pF.

Input resistance is 1 M Ω at all GAIN and ATTENUATOR settings, including the accessory plug-on attenuator head.

An AC coupling plug-on accessory features a 0.1 μ F coupling capacitor for each input. The low-frequency CMRR is reduced.

AUTOBALANCE

Holding both offset buttons down for two seconds with the input connections removed invokes Autobalance. This provides the highest accuracy on all ranges by removing residual DC offset from the probe.

LOW NOISE

At full gain, the noise is less than $4 \text{ nV}/\sqrt{\text{Hz}}$, the lowest of any available differential probe.

COMMON MODE SENSING AND INPUT PROTECTION

It is not uncommon for a differential amplifier to be connected to a signal whose common-mode voltage exceeds the amplifier's common-mode range. Faulty readings, including total loss of signal, can result. The AP033 senses when signals exceed $\pm 5.5 \text{ V}$ and switches its input attenuator into the signal path. The oscilloscope shows the new deflection factor, and the probe continues to work.

The same mechanism protects the probe from damage due to large input signals. The probe amplifier is protected from large, fast-rising signals until the input attenuator can provide permanent protection. This takes about 1 ms. With the input attenuator in place, the input can withstand 200 V DC indefinitely.

SPECIFICATIONS

Bandwidth: 500 MHz

Gain Range: x10, x1, $\div 10$ ($\div 100$ w/plug on $\div 10$ attenuator)

DC Accuracy: 1 % in 1x without external attenuator

Attenuator Range Accuracy: 0.2 %

Gain Range Accuracy: 1 %

Input Resistance: 1 M Ω (each input to ground), 2 M Ω Differential (between inputs)

Input Capacitance:

2 pF (each input to ground) ($\div 10$)

5 pF (each input to ground) ($\div 1$)

1.2 pF Differential (between inputs) ($\div 10$)

2.7 pF Differential (between inputs) ($\div 1$)

Input Voltage

Differential Max:

$\pm 40 \text{ V}$ ($\div 100$)

$\pm 4 \text{ V}$ ($\div 10$)

$\pm 400 \text{ mV}$ (x1)

$\pm 40 \text{ mV}$ (x10)

Common Mode Max: $\pm 42.4 \text{ V}$ AC peak or 50 V DC ($\div 10$), $\pm 5 \text{ V}$ ($\div 1$)

Max. Non-Destruct Voltage: $\pm 200 \text{ VDC}$ continuous

ESD Protection: $> 15 \text{ kV}$

CMRR: 10,000:1 (DC)

Warranty: Three years

ORDERING INFORMATION

Active Differential Probe 500 MHz
Optional ProBus™ to BNC Adapter and External Power Supply

Product Code

AP033
ADPPS

Sales and Service Throughout the World

Corporate Headquarters

700 Chestnut Ridge Road
Chestnut Ridge, NY 10977
USA
<http://www.lecroy.com>

LeCroy Sales Offices:

Asia South: Australia
Phone (61) 3 9877 9322
FAX (61) 3 9849 0861

Asia North: Hong Kong
Phone (852) 2836 7361
FAX (852) 2836 7007

France: Les Ulis
Phone (33) 1 69 18 83 20
FAX (33) 1 69 07 40 42

Germany: Heidelberg
Phone (49) 6221 827 00
FAX (49) 6221 834 655

Italy: Venice
Phone (39) 41 456 97 00
FAX (39) 41 456 95 42

Japan: Osaka
Phone (81) 6 396 0961
FAX (81) 6 396 0962

Japan: Tokyo
Phone (81) 3 3376 9400
FAX (81) 3 3376 9587

Japan: Tsukuba
Phone: (81) 298 41 5810
FAX: (81) 298 41 5830

Switzerland North: Niederlenz
Phone (41) 62 885 80 50
FAX (41) 62 885 80 55

Switzerland West: Geneva
Phone (41) 22 719 2228
FAX (41) 22 719 2230

U.K.: Abingdon
Phone (44) 1 235 536 973
FAX (44) 1 235 528 796

U.S.A.: Chestnut Ridge
Phone (1) 914 578 6020
FAX (1) 914 578 5985

Copyright © April 1998

LeCroy is a registered trademark of LeCroy Corporation. All rights reserved. Information in this publication supersedes all earlier versions. Specifications subject to change without notice.

DSAP033-E
0498
10MICA



LeCroy