

ABN 43 064 478 842

231 osborne avenue clayton south, vic 3169
 PO box 1548, clayton south, vic 3169
 t 03 9265 7400 f 03 9558 0875
 freecall 1800 680 680

www.tmgtestequipment.com.au

Test & Measurement

- sales
- rentals
- calibration
- repair
- disposal

Complimentary Reference Material

This PDF has been made available as a complimentary service for you to assist in evaluating this model for your testing requirements.

TMG offers a wide range of test equipment solutions, from renting short to long term, buying refurbished and purchasing new. Financing options, such as Financial Rental, and Leasing are also available on application.

TMG will assist if you are unsure whether this model will suit your requirements.

Call TMG if you need to organise repair and/or calibrate your unit.

If you click on the "Click-to-Call" logo below, you can all us for FREE!

TMG Corporate Website TMG Products Website Leuel 4 Disposal Disposal Click-to-Call TMG Now leuel 5 Review & Leuel 3 Repair Renew Review & Renew Repair Calibration Calibration Recycled Acquisition Leuel 1 Acquisition **Purchase** Lease Solution Centre Rent

Disclaimer:

All trademarks appearing within this PDF are trademarks of their respective owners.

Product Lifecycle Management System







169/Digital Multimeter

3½-Digit LCD Portable/Bench

- 2000-count display
- 1-year battery life
- Function & range annunciators Battery eliminator option

The Keithley 169 provides full capability for many general purpose applications. It has five functions: DC volts, DC amps, AC volts, AC amps and ohms. Input protection prevents damage on all functions. Voltage ranges are protected to 1400V peak, ohms is protected to 300V rms, and current ranges are protected by an externally accessible 2A (250V) fuse.

Easy to use. The 169 has both range and function annunciators. Pushbutton switches are color-coded to the front panel. Two input jacks and auto polarity mean no lead changing. Zeroing is automatic. Low battery condition is automatically indicated.

By using alkaline batteries, 2000 hours (1 year) of operation can be expected. Thus, battery life can be the same as the calibration cycle. Only 1 adjustment is required. MTBF is 20,000 hours, so most units will never need repair. If they do, all components are on one easily accessible PC board.



| DC VOLTS | | | |
|----------|------------|---|--|
| RANGE | RESOLUTION | ACCURACY (1 YEAR) 18°-28°C | |
| 200mV | 100 μV | . The yell to | |
| 2 V | 1mV | | |
| 20 V | 10mV | $\pm (0.25\% \text{ of reading} + 1 \text{ digit})$ | |
| 200 V | 100mV | | |
| 1000 V | 1 V | | |

MAXIMUM ALLOWABLE INPUT: 1000VDC, 1400V peak AC. INPUT RESISTANCE: 10MΩ.

NORMAL MODE REJECTION RATIO: Greater than 50dB at 50Hz, 60Hz. COMMON MODE REJECTION RATIO: Greater than 100dB at DC, 50Hz and 60Hz (1kΩ unbalance, 500V).

| C VOLTS | | S | ACCURACY (1 YEAR) 18°-28°C | |
|---------|----|------------|--|-------------------------------------|
| RAN | GE | RESOLUTION | 45Hz-1kHz | 1kHz-5kHz |
| 200r | nV | 100 μV | | |
| 2 | V | 1mV | | |
| 20 | V | 10mV | $\pm (0.75\% \text{ rdg} + 5\text{d})$ | $\pm (5\% \text{ rdg} + 7\text{d})$ |
| 200 | V | 100mV | | |
| 1000 | V | 1 V | | |

MAXIMUM ALLOWABLE INPUT: 1000V rms, 1400V peak, 10°V°Hz, continuous except 200mV range: 350V continuous, 15s maximum above

INPUT IMPEDANCE: 10MΩ shunted by less than 100pF.

RESPONSE: Average responding, calibrated in rms of a sine wave.

| DC AMPS | PEGOLUTION | ACCURACY (1 YEAR) | MAXIMUM VOLTAGE |
|---------|------------|--|--------------------|
| RANGE | RESOLUTION | 18°—28°C | BURDEN |
| 200 μΑ | 100 nA | | 0.25V |
| 2mA | 1 μΑ | | 0.25V |
| 20mA | 10 μΑ | $\pm (0.75\% \text{ rdg} + 1\text{d})$ | 0.25V |
| 200mA | 100 μΑ | | 0.3 V |
| 2000mA | 1mA | | 0.7 V |

OVERLOAD PROTECTION: 2A fuse (250V), externally accessible.

| AC AMPS RANGE | RESOLUTION | ACCURACY (1 YEAR) 18°-28°C (45Hz-1kHz) | MAXIMUM VOLTAGE BURDEN |
|---------------|------------|---|------------------------------|
| 200 μΑ | | | 0.25V rms |
| 2mA | | | 0.25V rms |
| 20mA | | $\pm (1.5\% \text{ rdg} + 5\text{d})$ | 0.25V rms |
| 200mA | | | 0.3 V rms |
| 2000mA | | | 0.7 V rms |

OVERLOAD PROTECTION: 2A fuse (250V), externally accessible.

| OHMS | | ACCURACY | |
|-------------|------------|---------------------------------------|-----------------------|
| RANGE | RESOLUTION | (1 YEAR) 18°-28°C | FULL SCALE VOLTAGE |
| 200 Ω | 100mΩ | $\pm (0.3\% \text{ rdg} + 3d)$ | < 0.5V |
| 2k Ω | 1 Ω | $\pm (0.2\% \text{ rdg} + 1\text{d})$ | < 0.5V |
| 20k Ω | 10 Ω | $\pm (0.2\% \text{ rdg} + 1\text{d})$ | > 0.7V |
| 200k Ω | 100 Ω | $\pm (0.2\% \text{ rdg} + 1\text{d})$ | > 0.7V |
| 2000k Ω | 1k Ω | $\pm (0.2\% \text{ rdg} + 1\text{d})$ | > 0.7V |
| $20M\Omega$ | 10k Ω | $\pm (2.0\% \text{ rdg} + 1\text{d})$ | > 0.7V |

MAXIMUM OPEN CIRCUIT VOLTAGE: 1.5V except 200Ω range: 3.5V. MAXIMUM ALLOWABLE INPUT: 300V DC or rms.

GENERAL

DISPLAY: 31/2-digit LCD, 0.6" numeral height, with polarity, range and function indicators.

OVERRANGE INDICATION: 3 least significant digits blanked.

MAXIMUM COMMON MODE VOLTAGE: 1400V peak.

OPERATING ENVIRONMENT: 0° to 50°C; less than 80% RH up to 35°C, less than 70% RH from 35° to 60°C.

STORAGE ENVIRONMENT: -35° to 60°C.

TEMPERATURE COEFFICIENT (0°-18°C & 28°-50°C): Less than 0.1 × applicable accuracy specification per °C.

POWER: Six 1.5V "C" cells.

BATTERY LIFE: 1000 hours typical with carbon zinc ceils; 2000 hours with alkaline cells

BATTERY INDICATOR: Display indicates "BAT" when less than 5% of life remains.

DIMENSIONS, WEIGHT: 85mm high \times 235mm wide \times 275mm deep (3 1 /2" \times 9 1 /4" \times 10 3 /4"). Net weight 1.4kg (3 lbs.).

ACCESSORIES AVAILABLE:

Model 1010: Single Rack Mounting Kit Model 1017: Dual Rack Mounting Kit

Model 1301: Temperature Probe

Model 1600A: High Voltage Probe

Model 1651: 50A Curent Shunt Model 1681: Clip-On Test Lead Set Model 1682A: RF Probe Model 1683: Universal Test Lead Kit

Model 1684: Hard Shell Carrying Case

Model 1685: Clamp-On Current Probe

Model 1691: General Purpose Test Leads Model 1699: Spare Parts Kit

Model 1766: Battery Eliminator

Model 1768: Battery Pack (for converting 169/1766 to battery power)