



ABN 43 064 478 842

➤ 231 osborne avenue clayton south, vic 3169
PO box 1548, clayton south, vic 3169
t 03 9265 7400 f 03 9558 0875
freecall 1800 680 680
www.tmgtestequipment.com.au

Test & Measurement

- sales
- rentals
- calibration
- repair
- disposal

Complimentary Reference Material

This PDF has been made available as a complimentary service for you to assist in evaluating this model for your testing requirements.

TMG offers a wide range of test equipment solutions, from renting short to long term, buying refurbished and purchasing new. Financing options, such as Financial Rental, and Leasing are also available on application.

TMG will assist if you are unsure whether this model will suit your requirements.

Call TMG if you need to organise repair and/or calibrate your unit.

If you click on the “Click-to-Call” logo below, you can call us for FREE!

TMG Corporate Website

TMG Products Website



Click-to-Call
TMG Now



Disclaimer:

All trademarks appearing within this PDF are trademarks of their respective owners.

Technical Information

Power Sensors R&S NRP-Z51, -Z55

Thermoelectric accuracy at its best

The new power sensors for the frequency ranges DC to 18 GHz (R&S NRP-Z51) and DC to 40 GHz (R&S NRP-Z55) for the first time combine the thermoelectric test cell with a complete power meter. The sensors feature not only all the advantages of the thermal measuring principle but also a further increase in accuracy since the influence of the base unit is eliminated; they also offer a continuous measurement range from 1 μ W to 100 mW without range switching, f correction to reduce matching

errors and numerous other assets. The DC-coupled thermal test cell of the predecessor models R&S NRV-Z51 and R&S NRV-Z55 was adopted, allowing measurements starting at 0 Hz, plus reference to a low-frequency or DC standard. Like the other sensors of this instrument family, the new sensors can be operated via the R&S NRP base unit or a PC with a USB interface. A virtual user interface is part of the equipment supplied to enable operation from a PC.



ROHDE & SCHWARZ

Preliminary

Power Sensors R&S NRP-Z51, -Z55

Specifications

(data above 18 GHz apply to R&S NRP-Z55 only)

Bold: Parameter 100% tested

Italics: Uncertainties calculated from the test assembly specifications and the modelled behaviour of the sensor.

Normal: Compliance with specifications is ensured by the design or derived from the measurement of related parameters

Sensor type		Thermoelectric sensor	
Measurand		Average power of incident wave average power of source into 50 Ω ¹⁾	
Frequency range		DC to 18 GHz (R&S NRP-Z51) DC to 40 GHz (R&S NRP-Z55)	
Matching (SWR)	DC to 2.4 GHz > 2.4 GHz to 12.4 GHz > 12.4 GHz to 18.0 GHz > 18.0 GHz to 26.5 GHz > 26.5 GHz to 40.0 GHz	< 1.10 < 1.15 < 1.20 < 1.25 < 1.30	
RF connector		N (male) for R&S NRP-Z51 2.92 mm (male) for R&S NRP-Z55	
Power measurement range		1 μ W to 100 mW (-30 dBm to +20 dBm) cont., without subranges	
Max. power	Average Pulse energy	0.3 W (+25 dBm) continuous 10 W μ s	
Display noise ¹⁴⁾		< 30 nW (20 nW typ.)	
Zero offset ¹⁷⁾		< 50 nW (33 nW typ.)	
Zero drift ¹⁸⁾		< 20 nW	
Linearity uncertainty ^{*)}		< 0.02 dB	
Calibration uncertainty ^{**) at (20 to 25°C)}	10 MHz to < 100 MHz 100 MHz to 4 GHz > 4 GHz to 8 GHz > 8 GHz to 12.4 GHz > 12.4 GHz to 18 GHz > 18.0 GHz to 26.5 GHz > 18.0 GHz to 30.0 GHz > 30.0 GHz to 35.0 GHz > 35.0 GHz to 40.0 GHz	R&S NRP-Z51 <i>0.047 dB</i> <i>0.057 dB</i> <i>0.071 dB</i> <i>0.076 dB</i> <i>0.098 dB</i>	R&S NRP-Z55 <i>0.053 dB</i> <i>0.065 dB</i> <i>0.077 dB</i> <i>0.084 dB</i> <i>0.104 dB</i> <i>0.086 dB</i> <i>0.100 dB</i> <i>0.112 dB</i> <i>0.105 dB</i>
Temperature effect		< 0.004 dB/K (0.001 dB/K typ.)	

Uncertainty for absolute power measurements ^{***)} from -13 dBm to 20 dBm	R&S NRP-Z51	20°C to 25°C	15°C to 35°C	0°C to 50°C
	10 MHz to < 100 MHz 100 MHz to 4 GHz > 4 GHz to 8 GHz > 8 GHz to 12.4 GHz > 12.4 GHz to 18 GHz	0.052 dB 0.061 dB 0.074 dB 0.078 dB 0.100 dB	0.057 dB 0.066 dB 0.078 dB 0.082 dB 0.102 dB	0.075 dB 0.082 dB 0.092 dB 0.095 dB 0.113 dB
	R&S NRP-Z55	20°C to 25°C	15°C to 35°C	0°C to 50°C
	10 MHz to < 100 MHz 100 MHz to 4 GHz > 4 GHz to 8 GHz > 8 GHz to 12.4 GHz > 12.4 GHz to 18 GHz > 18.0 GHz to 26.5 GHz > 18.0 GHz to 30.0 GHz > 30.0 GHz to 35.0 GHz > 35.0 GHz to 40.0 GHz	0.057 dB 0.068 dB 0.080 dB 0.084 dB 0.106 dB 0.092 dB 0.102 dB 0.114 dB 0.108 dB	0.062 dB 0.072 dB 0.083 dB 0.087 dB 0.108 dB 0.095 dB 0.104 dB 0.116 dB 0.110 dB	0.079 dB 0.087 dB 0.096 dB 0.100 dB 0.119 dB 0.106 dB 0.115 dB 0.126 dB 0.1203 dB

Measurement window ⁷⁾	Duration Shape	2 × (1 ms to 300 ms) rectangular (integrating behaviour) Von Hann (smoothing filter, for efficient suppression of result variations due to modulation ²⁶⁾)
Measurement time ²⁷⁾		N × (duration of measurement window + 0.5 ms) + t _z t _z : < 82 ms
Zeroing (duration)	Depends on setting of averaging filter AUTO ON AUTO OFF Integration time ¹⁶⁾ < 4 s 4 s...16 s > 16 s	4 s 4 s integration time ¹⁶⁾ 16 s
Averaging filter	Modes Normal operating mode ²³⁾ Resolution Fixed Noise operating mode Noise content Max. measurement time ²⁴⁾ Averaging factor N Result output Moving Average Repeat	AUTO OFF (fixed averaging factor) AUTO ON (continuously auto-adapted) AUTO ONCE (automatically fixed once) setting of filter depends on power to be measured and resolution 1 (1 dB), 2 (0.1 dB), 3 (0.01 dB), 4 (0.001 dB) filter set to specified noise content 0.0001 dB to 1 dB 0.01 s to 1000 s 1 to 2 ¹⁶ (number of averaged measurement windows) continuous with every newly evaluated measurement window (e.g. in case of manual operation via R&S NRP) only final result (e.g. in case of remote control of R&S NRP)
Duty cycle correction ⁸⁾		0.001 % to 99.999 %

Capacity of measurement buffer ⁹⁾		1 to 1024 results
Triggering	Source Slope (external, internal) Level Internal External Delay Holdoff Hysteresis	Bus, External, Hold, Immediate, Internal pos./neg. -16 dBm to +20 dBm see specs of R&S NRP and USB Adapter R&S NRP-Z3 0 s to +100 s 0 s to 10 s 0 dB to 10 dB
Attenuation correction	Function Range	Correcting the measurement result by means of a fixed factor (dB offset) -100.000 dB to +100.000 dB
S-parameter-correction	Function Number of frequencies Parameters Download	taking into account a component connected ahead of the sensor by loading ist s-parameter data set into the sensor 1 to 1000 S_{11} , S_{21} , S_{12} and S_{21} (in s2p format) with R&S NRP Toolkit (supplied with sensor) via USB Adapter R&S NRP-Z3 or R&S NRP-Z4.
Γ correction	Function Parameters Download	reducing the influence of mismatched sources ²⁹⁾ magnitude and phase of reflection coefficient of source see under S-parameter correction
Frequency response correction	Function Parameter Permissible deviation from actual value	taking into account the calibration factors relevant for the test frequency Carrier frequency (center frequency) 100 MHz ($0.1 \times f$ below 1GHz) for specified measurement uncertainty
Interface to host	Power supply Remote control Trigger input	+5 V / 100 mA typ. (USB Low-power device) as a USB device (function) in full-speed mode, compatible with USB 1.0/1.1/2.0 specifications differential (0 / +3.3 V)
Dimensions (W × H × L)		48 mm × 31 mm × 170 mm length incl. connecting cable: approx. 1.6 m
Weight		< 0.3 kg

*) For relative measurements referenced to 0 dBm.

**) Expanded uncertainty (k=2) for absolute power measurements at the calibration level (0 dBm) and the calibration frequencies (10 MHz, 50 MHz, 100 MHz; from 500 MHz to 18 GHz in increments of 500 MHz). Specifications include zero offset and display noise (up to a 2σ value of 0.004 dB).

***) Includes the effects of calibration uncertainty, linearity, zero offset, temperature and display noise (up to a value of 0.004 dB). For power levels below -13 dBm the effect of zero set must be calculated separately.

General specifications

see the R&S NRP data sheet (PD 0757.7023.21), sensors R&S NRP-Z11/-Z21.

Accessories and numerical footnotes

see the R&S NRP data sheet (PD 0757.7023.21)

Ordering information

Description	Type	Order No.
Power Sensor 1 μ W to 100 mW; DC to 18 GHz	R&S NRP-Z51	1138.0005.02
Power Sensor 1 μ W to 100 mW; DC to 40 GHz	R&S NRP-Z55	1138.2008.02

