

ABN 43 064 478 842

231 osborne avenue clayton south, vic 3169 PO box 1548, clayton south, vic 3169 t 03 9265 7400 f 03 9558 0875 freecall 1800 680 680 www.tmgtestequipment.com.au

# Test & Measurement

#### sales

- rentals
- calibration
- repair
- disposal

# **Complimentary Reference Material**


This PDF has been made available as a complimentary service for you to assist in evaluating this model for your testing requirements.

TMG offers a wide range of test equipment solutions, from renting short to long term, buying refurbished and purchasing new. Financing options, such as Financial Rental, and Leasing are also available on application.

TMG will assist if you are unsure whether this model will suit your requirements.

Call TMG if you need to organise repair and/or calibrate your unit.

If you click on the "Click-to-Call" logo below, you can all us for FREE!



#### **Disclaimer:**

All trademarks appearing within this PDF are trademarks of their respective owners.







## FIBER INSPECTION PROBE

# FIP-400

NETWORK TESTING-OPTICAL



# Highly versatile probe to detect dirty/damaged connectors with unparalleled precision

- Easy back-panel connector inspection
- Truly rugged and lightweight solution for the field
- Image-capture capability for report documentation (.jpg)
- Ideal for all types of connectors: APC, UPC, MTP and more
- Slim design for easy use in crowded patch panels
- Compatible with EXFO test instruments
- USB adapter




# Zoom In on Clarity

It's a known fact: optical network problems are often caused by dirty and/or damaged connectors. Using a fiber inspection probe to ensure connectors/adapters are clean and exempt of any defect is where accurate testing starts.

Thanks to EXFO's FIP-400 Fiber Inspection Probe, checking connectors and other fiber terminations for polish quality and cleanliness has never been easier. Benefit from the best optical resolution in the industry and see scratches and dirt particles as small as 1  $\mu m$ .



Magnification and focus controls



#### FIBER PROBE VIEWER

#### **VIDEO INSPECTION PROBE**



# The Industry's Most Versatile Probe

With EXFO's FIP-400, you have the choice—you can either use it with a PC, with one of our test sets or with our lightweight, handheld monitor. Choose the way that works for you.



# **Applications**

#### **Patchcord inspection**

- Compatible with a wide range of connector types
- Offers great optical performance for patchcord quality assurance
- Use it as a stand-alone unit to perform field applications or with a USB adapter in a manufacturing environment

#### Patch panel bulkhead inspection

- Get a clear view of both sides of an interconnection
- Inspect hard-to-reach connectors without stressing adjacent fibers, thanks to the FIP-400's slim design

#### Single fiber connector inspection

Compatible with 1.25 mm and 2.5 mm angled-polished and ultra polished connectors (APC and UPC)

#### Multifiber connector inspection

Compatible with male and female ribbon connectors such as MTP multifiber APC and UPC connectors



Patchcord inspection in a manufacturing environment



Patch panel bulkhead inspection

#### **ADAPTER TIPS**



#### FIPT-400 ADAPTER

Adapter tip



#### FITP-400-FC-SC-APC

FC and SC tip for APC bulkheads



#### FIPT-400-U25M

Universal patchcord tip for 2.5 mm ferrules



## FIPT-400-ST

ST tip for bulkhead adapters



#### FIPT-400-U25MA

Universal patchcord tip for 2.5 mm APC ferrules



### FIPT-400-LC

LC tip for bulkhead adapters



#### FIPT-400-U12M

Universal patchcord tip for 1.25 mm ferrules



#### FIPT-400-LC-APC

FIPT-400-U12MA

APC ferrules

LC/APC tip for bulkhead adapters

Universal patchcord tip for 1.25 mm



#### FIPT-400-MTP

adapters

FIPT-400-FC-SC

MTP tip for PC bulkheads

FC and SC APC tip for bulkhead



#### FIPT-400-MTPA

MTP tip for PC bulkheads

FIPT-400-LC-KIT = FITP-400-LC, FITP-400-LC-APC, FITP-400-U12M, FITP-12MA FIPT-400-25A-KIT = FITP-400-U25MA, FIPT-400-FC-SC-APC

#### **SPECIFICATIONS**

Video Inspection	Probe	
Size (L x W x H)	170 mm x 32 mm x 38.5 mm (without tip cap)	
	200 mm x 32 mm x 38.5 mm (with tip cap)	
Weight	0.2 kg (0.44 lb)	
Camera type	0.25 in CCD	
Resolution	Theoretical < 2 µm, detection capability < 1 µm	
Field of view	0.625 μm x 0.464 μm (low magnification)	
	0.412 μm x 0.316 μm (high magnification)	
Light source	Blue LED	
Lighting technique	Coaxial	
Capture button <sup>a</sup>	Present on all models	
Connector	EXFO probe port type (8 pin mini-DIN)	
Focus control	Adjustable on the probe	

Fiber Probe Viewer			
Size (L x W x H)	190 mm x 99 mm x 50 mm		
Weight b	0.3 kg (0.66 lb)		
LCD	3.5 in TFT active matrix (320 x 240 pixels)		
Power	Rechargeable Li-lon battery or AC adapter/charger		
	110 or 240 VAC-9VDC at 1 A		
Battery life	3 hours (continuous use)		
Charging time	4 hours		
Connector	EXFO probe port type (8 pin mini-DIN)		
USB Converter	USB 1.1 model	USB 2.0 model	
Size (L x W x H)	90 mm x 36 mm x 20 mm	95 mm x 36 mm x 19 mm	
Connectors	EXFO probe port type (8 pin mini-DIN)/USB		
Capture button	No	Yes	

#### GENERAL SPECIFICATIONS

02.12.0.12.0.	92.12.1.12.01.2011.10110				
Temperature					
operating	−10 to 50 °C				
storage	-40 to 70 °C				
Relative humidity	0 % to 95 % non-condensing				

Optical magnification Adjustable, low and high (dual model only)

#### ORDERING INFORMATION

#### **PROBE**

#### FIP-400-P-XX-XX

Model \_\_\_

FIP-400-P-SINGLE = video inspection probe single magnification

FIP-400-P-DUAL = video inspection probe dual magnification

#### **Standard Accessories**

- Video inspection probe (single or dual magnification)
- = FC-SC tip for bulkheads
- U25M universal patchcord tip for 2.5 mm ferrules
- Plastic case divided into various compartments for tips

Example: FIP-400-P-SINGLE-FIPT-400-LC

- a. Works with USB 2.0 adapter, FOT-930 and FTB-200
- b. Without battery
- c. See adapter tips list

#### **DISPLAY**

#### FIP-400-D

Model \_\_\_\_

FIP-400-D = Handheld display

Example: FIP-400-D

#### **USB**

#### FIP-400-USBX

Model -

FIP-400-USB1 = USB1 converter with software,

compatible with FTB-400

FIP-400-USB2 = USB2 converter with software

Example: FIP-400-USB1

#### **OPTIONAL ACCESSORIES**

FIPT-BOX = plastic case divided into various compartments for tips

GP-1001 = rechargeable battery for handheld display

GP-10-073 = soft carrying case for inspection probe, display and accessories

#### Rugged Handheld Solutions

- **OPTICAL** OTDRs
- OLTSs
- Power meters Light sources Talk sets
- COPPER ACCESS ADSL/ADSL2+, SHDSL, VDSL test sets

Adapter tips of Adapter tips of Adapter tips

- VolP and IPTV test sets
- Ethernet test sets - POTS test sets



#### Platform-Based Solutions

- OPTICAL FIBER
- OTDRs
- OLTSs ORL meters
- Variable attenuators
- DWDM TEST SYSTEMS TRANSPORT AND DATACOM
- OSAs Chromatic dispersion analyzer
- -PMD analyzers
- Next-generation SONET/SDH and OTN testers
  SONET/DSn (DS0 to OC-192) testers
  - SDH/PDH (64 kbit/s to STM-64) testers
  - -T1/T3. E1 testers
  - 10/100 Mbit/s and Gigabit Ethernet testers
  - Fibre Channel testers

#### EXFO Corporate Headquarters > 400 Godin Avenue, Quebec City (Quebec) G1M 2K2 CANADA | Tel.: 1 418 683-0211 | Fax: 1 418 683-2170 | info@EXFO.com

Toll-free: 1 800 663-3936 (USA and Canada) | www.EXFO.com EXFO America 3701 Plano Parkway, Suite 160 Plano, TX 75075 USA Tel.: 1 800 663-3936 Fax: 1 972 836-0164 EXFO Europe Omega Enterprise Park, Electron Way Chandlers Ford, Hampshire S053 4SE ENGLAND Tel.: +44 2380 246810 Fax: +44 2380 246801 **EXFO** Asia 151 Chin Swee Road, #03-29 Manhattan House SINGAPORE 169876 Tel.: +65 6333 8241 Fax: +65 6333 8242 EXFO China No. 88 Fuhua, First Road, Central Tower, Room 801 Shenzhen 518048 P. R. CHINA Tel.: +86 (755) 8203 2300 Fax: +86 (755) 8203 2306 Beijing New Century Hotel Office Tower, Room 1754-1755 Beijing 100044 P. R. CHINA Tel.: +86 (10) 6849 2738 Fax: +86 (10) 6849 2662 No. 6 Southern Capital Gym Road

EXFO is certified ISO 9001 and attests to the quality of these products. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. EXFO has made every effort to ensure that the information contained in this specification sheet is accurate. However, we accept no responsibility for any errors or omissions, and we reserve the right to modify design, characteristics and products at any time without obligation. Units of measurement in this document conform to SI standards and practices. In addition, all of EXFO's manufactured products are compliant with the European Union's WEEE directive. For more information, please visit www.EXFO.com/recycle. Contact EXFO for prices and availability or to obtain the phone number of your local EXFO distributor.

For the most recent version of this spec sheet, please go to the EXFO website at http://www.EXFO.com/specs In case of discrepancy, the Web version takes precedence over any printed literature.





