



ABN 43 064 478 842

231 Osborne Avenue Clayton South, VIC 3169
PO Box 1548, Clayton South, VIC 3169
t 03 9265 7400 f 03 9558 0875
freecall 1800 680 680
www.tmgtestequipment.com.au

Test & Measurement

- > sales
- > rentals
- > calibration
- > repair
- > disposal

Complimentary Reference Material

This PDF has been made available as a complimentary service for you to assist in evaluating this model for your testing requirements.

TMG offers a wide range of test equipment solutions, from renting short to long term, buying refurbished and purchasing new. Financing options, such as Financial Rental, and Leasing are also available on application.

TMG will assist if you are unsure whether this model will suit your requirements.

Call TMG if you need to organise repair and/or calibrate your unit.

If you click on the "Click-to-Call" logo below, you can call us for FREE!

TMG Corporate Website

TMG Products Website



Click-to-Call
TMG Now



Product Lifecycle Management System

Disclaimer:

All trademarks appearing within this PDF are trademarks of their respective owners.



MS-2

Circuit Breaker and Overload Relay Test Set



- **Digital memory ammeter**
- **Digital, multirange timer**
- **High-current output**
- **Solid-state output initiate circuit**
- **Portable, high-current test set**

DESCRIPTION

The MS-2 test set is used around the world by several thousand utility companies, industrial plants and electrical service organizations.

Using the latest technology, Model MS-2 is a self-contained test set that incorporates a variable high-current output and appropriate control circuitry and instrumentation for testing thermal, magnetic or solid-state motor overload relays; molded-case circuit breakers; and ground-fault trip devices.

APPLICATIONS

Model MS-2 is capable of testing the time-delay characteristics of motor overload relays and molded-case circuit breakers rated up to 125 amperes, when following the recommended test procedure of testing the time delay of these devices at three times their rating.

Higher currents are available for the short durations required to test an instantaneous trip element. For example, the test set will provide a maximum short-duration output of 750 amperes through a typical, 125 ampere, molded-case circuit breaker.

Additional applications include verifying the ratio of current transformers and testing panelboard ammeters and voltmeters.

FEATURES AND BENEFITS

- **Digital memory ammeter:** High-accuracy, direct-reading instrument has read-and-hold memory for measurement of short-duration currents.
- **Digital, multirange timer:** Crystal-controlled, high-accuracy instrument with autoranging measures operating time to 1 millisecond.
- **High-current output:** Provides instantaneous currents up to 750 amperes through a 125 ampere breaker.
- **Rugged and lightweight:** Unit weighs only 33 lb (15 kg) and is tough enough to withstand daily field or plant use.
- **Solid-state output initiate circuit:** Solid-state circuit eliminates need for contact maintenance.

SPECIFICATIONS

Input

Input Voltage (specify one): 120 V OR 240 V, 50/60 Hz, 1 ϕ

Output

Output Ranges: The output is continuously adjustable in four ranges to accommodate a variety of test-circuit impedances:
 0 to 5 A at 120 V max.
 0 to 25 A at 24 V max.
 0 to 120 A at 6 V max.
 0 to 240 A at 3 V max.

Output Capacity: The output circuit is designed to permit short-duration overloads and the output ranges will provide several times their current rating, provided the output voltage is sufficient to push the desired current through the impedance of the test circuit.

The test set is capable of testing the time-delay characteristics of devices rated up to 125 A using a test current of three times their rating (375 A). Additionally, to perform an instantaneous trip test, it will provide 750 A through a typical, 125 A, molded-case circuit breaker connected with the test leads provided with the test set.

Overload Capability: To increase use of the test set, it is designed so that the current ratings may be exceeded for short durations. Because the magnitude of the output current is determined by the impedance of the load circuit, the voltage rating must be sufficient to push the desired current through the device under test and the connecting test leads.

Percent Rated Current	Maximum Time On	Minimum Time Off
100 (1x)	30 min	30 min
200 (2x)	3 min	8 min
300 (3x)	30 s	4 min
400 (4x)	7 s	2 min

Output Initiate Circuit: The test set uses a solid-state output initiating circuit. To increase reliability and eliminate contact maintenance, this circuit uses a triac instead of a contactor to initiate the output.

The initiating circuit provides momentary and maintained modes to control output duration. The momentary mode is used whenever the output is to be on for a short duration, such as when performing instantaneous trip tests, or to avoid damage or overheating of the device under test while setting the test current. In the maintained mode, the output remains energized until manually turned off or, when performing timing tests, until the device under test operates — which both stops the timer and de-energizes the output.

INSTRUMENTATION

Ammeter

Operating Modes (switch-selected)

Memory
Normal

Display

3½ digit, extra-bright LED display with 0.3 in. (7.62mm) numerals

Ranges (switch-selected)

0 to 1.999/19.99/199.9/750 A

Continuous Accuracy (overall ammeter system)

±1% of reading, ±1 digit on three high ranges

Regulating: ±1% of range, ±1 digit on low range

Timer

Display

5-digit, extra-bright, LED display with 0.3 in. (7.62mm) numerals

Ranges (switch-selected)

0 to 99.999 s

0 to 999.99 s

0 to 99999 cycles

Accuracy

±0.005% of reading, ±1 digit

Timer Control Circuit

This circuit automatically starts the timer when the output is energized and automatically stops the timer and de-energizes the output when the device under test operates. This circuit accommodates the following test conditions by simple switch selection of the appropriate mode:

Current Actuated: Used to test a device that has no auxiliary contacts to monitor, such as a single-pole circuit breaker. The timer stops when the output current is interrupted.

Normally Closed: Used to test a device with normally closed contacts. The timer stops and the output is de-energized when the contacts open.

Normally Open: Used to test a device with normally open contacts. The timer stops and the output is de-energized when the contacts close.

Enclosure

The test set is housed in a high strength, molded, suitcase-type enclosure with carrying handle and removable cover. Storage space is provided for test leads.

Dimensions

9.9 H x 14 W x 11 D in.

(25 H x 35 W x 28 D cm)

Weight

33 lb (15 kg)

ORDERING INFORMATION

Item (Qty)	Cat. No.
Model MS-2	
115 volt input	MS-2-115
230 volt input	MS-2-230
Included Accessories	
Timer control circuit leads, 5 ft (1.5 m) [2]	1282
Test and maintenance record cards	
Green [50]	2239
Buff [50]	2238

Item (Qty)	Cat. No.
No. 4 high-current leads, 5 ft (1.5 m) [2]	2265
Fuses	
5 A, 250 V, MDA [5]	952
0.125 A, 250 V, MDL [5]	981
10 A, 250 V, MDA [5]	984
0.0625 A, 250 V, MDL [5]	987
Instruction manual [1]	8470

UK

Archcliffe Road Dover
CT17 9EN England
T +44 (0) 1304 502101
F +44 (0) 1304 207342

UNITED STATES

4271 Bronze Way
Dallas TX75237-1088 USA
T 800 723 2861 (USA only)
T +1 214 330 3203
F +1 214 337 3038

OTHER TECHNICAL SALES OFFICES

Valley Forge USA, Toronto CANADA,
Mumbai INDIA, Trappes FRANCE,
Sydney AUSTRALIA, Madrid SPAIN
and the Kingdom of BAHRAIN.

Registered to ISO 9001:2000 Reg no. Q 09290

Registered to ISO 14001 Reg no. EMS 61597

MS2_DS_en_V10

www.megger.com
Megger is a registered trademark